

SP-64 , SP-126 Simplicity Plus Analogue Addressable Fire Alarm Panel

Complies with EN54 Pt 2, 4



The Simplicity Plus is the ideal introduction to the world of addressable fire alarm panels.

As its name suggests, it has been designed with ease of use in mind, using pre-programmed values for its programming options. The installer simply needs to configure the loop, and enter text labels via the built in keyboard.

The Simplicity Plus is available in 64 device, and 126 device versions, and now includes a real time clock, and 2048 capacity event log. It can also be connected to an RS232 desktop printer for real time event log printing. (Epson LQ300+ recommended).

It can also drive a serial repeater model AD-REP, part no. 37-156.

Loop & Address	SP-126	SP-64
1: Address 1-16	Zone 1	Zone 1
1: Address 17-32	Zone 2	Zone 2
1: Address 33-48	Zone 3	Zone 3
1: Address 49-64	Zone 4	Zone 4
1: Address 65-80	Zone 5	-
1: Address 81-96	Zone 6	-
1: Address 97-112	Zone 7	-
1: Address 113-126	Zone 8	-

MODEL	SP-64	SP-126
PART NO	37-160	37-165
SUPPLY VOLTAGE	230V AC +/- 10%	230V AC +/- 10%
SYSTEM VOLTAGE	24V DC (NOMINAL)	
NUMBER OF LOOPS	1	
LOOP CAPACITY	64 DEVICES	126 DEVICES
NUMBER OF ZONES	4	8
SOUNDER OUTPUT	ADDRESSABLE SOUNDERS ONLY	
FAULT OUTPUT	28 V REPEAT OUTPUT TO DRIVE RELAY (NORMALLY ENERGISED)	
FIRE OUTPUT	28 V REPEAT OUTPUT TO DRIVE RELAY	
OPERATING TEMPERATURE	-0° C to 50° C	
ENCLOSURE SIZE	355 X 275 X 100mm	
WEIGHT	3.5 KG	